

## Loading Sounds and Demos from a PCMCIA Card



Use the instructions below to load demos into the A and B Internal Banks of the MS-1. This procedure will erase all sound and sequence data presently in the MS-1's internal memory. Refer to the MS-1 Owner's Manual, Chapter 7 or Chapter 9, for instructions on saving data to a PCMCIA card or via MIDI.

- 1) Turn off the MS-1.
- 2) Insert the PCMCIA Card into the card slot.
- 3) Turn on the MS-1.
- 4) Press UTILITY.
- 5) Scroll with the right or left cursor arrow buttons until you get to the Load:BUF\_\_ screen.
- 6) Select the backup file that you want to load with the - or + buttons.
- 7) After selecting the backup file that you want press YES. The MS-1 will count down from eight and the screen will come back to Bank A.
- 8) The backup file should now be loaded and accessible from either the pad or sequence mode of the MS-1.
- 9) To play the sequence press SEQ, then press the Play pad.